

EAN: 6414150075094 [static.oras.com/199502](http://static.oras.com/199502)

The bus transformer is designed to be used with Oras products No. 6661FTX, 6662FTX and 6664FTX. A maximum of 10 shower panels can be connected to the transformer at a time. Shower panels can be switched off at the transformer's ON/OFF switch for cleaning and maintenance operations. An automatic disinfection flush can be activated by an integrated switch. If there is a power cut, the transformer automatically turns off any shower panels that are on. Equipped with an option that enables external control of a cleaning mode and automatic disinfection flushing. Transformer installation must be carried out by a qualified electrician.

- Accessories, Health & Care, Public & Semi-public
- Black
- The bus transformer is designed to be used with Oras products No. 6661FTX, 6662FTX and 6664FTX. A maximum of 10 shower panels can be connected to the transformer at a time. Shower panels can be switched off at the transformer's ON/OFF switch for cleaning and maintenance operations. An automatic disinfection flush can be activated by an integrated switch. If there is a power cut, the transformer automatically turns off any shower panels that are on. Equipped with an option that enables external control of a cleaning mode and automatic disinfection flushing. Transformer installation must be carried out by a qualified electrician.



## TECHNICAL DATA

### ELECTRONIC PROPERTIES

Electrical Connection **230 VAC**

### REGULATIONS

EU Directives **CE Low Voltage Directive 2014/35/EU , EMC Directive 2014/30/EU , RoHS Directive 2011/65/EU**

EN standard **ETSI EN 301 489-1 V1.9.2 , ETSI EN 300 328 v2.2.2 , EN 61000-6-1:2007 , EN 61000-6-3:2007+A1:2011+AC:2012 , EN 60335-1:2012+A11+A13+A14+A15:2021, Part 19.11.4**

Protection class **IP 40**

### APPROVALS AND DECLARATIONS

Declaration of conformity **LVD**

